

December 7, 2000
1998P05883WO

- 1 -

DE 00990380

PCT Chapter II

MU DG 2

Description

- 5 Method for data transmission in a mobile radio system;
mobile station and base station

10 The invention relates to a base station, a
mobile station and a method for data transmission in a
communication system, in particular in a CDMA mobile
radio system, with the data being transmitted
structured into frames in such a manner that it is
possible for a mobile station to carry out other
functions, in particular to carry out measurements via
15 a receiving device, during one or more interruption
phases in which it interrupts the reception (of the
previous source or of the data from the base station)
and/or the processing of received data or the
transmission process. In the following text, the term
20 "transmission" refers to both sending and/or receiving.

25 In communications systems, data (for example
voice data, image data or system data) are transmitted
on transmission paths between base stations and mobile
stations. In radio communications systems, this is done
with the aid of electromagnetic waves via an air or
radio interface. In this case, carrier frequencies are
used which lie in the frequency band provided for the
respective system. The carrier frequencies for GSM
(Global System for Mobile Communication) are in the
30 band around 900 MHz. Frequencies in the frequency band
around 2000 MHz are being provided for future radio
communications systems, for example the UMTS (Universal
Mobile Telecommunication System), which uses a CDMA
(Code Division Multiple Access System) method, or other
35 third-generation systems.

Particularly in future CDMA systems, the base
station will transmit essentially continuously, for

AMENDED SHEET

09857653-060701

December 7,
2000
1998 P05883 WO

- 1a -

DE 00990380

example, in the downlink direction, that is to say in
the direction from base station to a mobile station.
The data transmitted

09857653-060701
T07090-65975860

AMENDED SHEET

during transmission are normally structured into frames, which each have a predetermined length. The frames may also have a different structure and length, particularly for different services, such as voice data transmission and video data transmission. The structure and/or length of each frame in a continuous sequence of frames is, however, predetermined and/or is recognized by the mobile station.

In cellular mobile systems in particular, the mobile station occasionally also has to carry out functions other than data reception, which cannot be carried out at the same time, at least when using only a single receiving device. For example, the mobile station in a cellular radio communications system in which the base stations in different cells transmit at different frequencies, from time to time, has to measure whether the radio signals from another base station can be received with good reception quality. To do this, the mobile station sets its receiving device to a different frequency than the frequency at which it is currently receiving data.

In order to allow transmission without interruption from the base station to the mobile station, it has already been proposed for the mobile station to be equipped with a second receiving device. However, this solution is generally rejected in practice, for cost reasons.

Another proposal is known from WO-A 9725827, according to which the base station interrupts the transmission at predetermined times in order to allow the receiving station to use its single receiving device to carry out an adjacent channel search or adjacent channel monitoring (search for an adjacent base station or for specific data packets transmitted by these base stations, which, in the following text, may also be considered to include synchronization, frequency correction or pilot signal bursts).

In order to avoid loss of data, the base station first of all transmits the data at a higher transmission rate than the essentially constant continuous transmission rate. To prevent this leading to increased bit error rates (BER), the transmission power also needs to be
5 increased during this time.

The frequency at which the interruption phases recur and the length of the interruption phases depend on the respective system and on the respective
10 operating state of the system, as well. Since the deterioration in the transmission quality also increases with the number of interruption phases inserted, it is desirable to insert as few interruption phases as possible, or for the interruption phases to
15 be as short as possible.

The object of the present invention is now to specify a method for data transmission in a mobile radio system, a mobile station and a base station, which allows reliable adjacent channel monitoring with
20 a smaller number of interruption phases than in the prior art.

The object is achieved by the independent patent claims. Developments are the subject matter of the dependent claims.

Accordingly, the invention is based on the
25 idea, during interruption phases which are inserted into a data stream for synchronization purposes, not only of switching to reception of characteristic data packets, but also of switching to reception of data
30 packets which are to be detected.

Thus, for example, while data are being transmitted in the downlink direction from a first base station to a mobile station, interruption phases are inserted at least during specific transmission phases,
35 in which interruption phases the mobile station interrupts the reception of the data transmitted by the first base station and/or interrupts the processing of the received data or the

transmission process, the mobile station is switched to reception of characteristic data packets and data packets which are to be detected and are transmitted by a second base station.

5 It is thus possible to keep the number and/or duration of interruption phases to be inserted low by utilizing the known frame structure of data transmission from the second base station to the mobile station. It is thus possible to reduce the required
10 effective total duration of the interruption phases, and thus to improve the transmission quality.

 A first transmission method, which is used by a first base station, may in this case be a CDMA method, and a second transmission method, which is used by a
15 second base station, may be a GSM method. The invention may in this case be part of an uplink or downlink overall concept for a GSM-UMTS dual-mode mobile radio system.

 One development of the invention provides for
20 information which influences the insertion of interruption phases to be transmitted by the mobile station to the first base station as a function of a reception result which is achieved during the interruption phases in which the receiving device is
25 switched to reception of data packets from the second base stations. The reference to influencing the insertion of interruption phases also means limiting the number of future interruption phases and/or ending the insertion of interruption phase and/or controlled
30 continuation of the insertion of further interruption phases and/or controlling the duration of the interruption phases.

 It is thus possible to end the insertion of interruption phases as soon as possible and thus to
35 limit it as much as possible as soon as sufficient information about the second

09857653-060701
T02090-5525860

base stations to be monitored is known, and hence to improve the transmission quality.

Another development variant of the invention provides for the mobile station to be switched successively to reception of data packets from a number of base stations and, as a function of the reception results, for information which influences the insertion of the interruption phases to be transmitted to the first base station.

This makes it possible to monitor a number of adjacent base stations successively, and initially to end the insertion of interruption phases once they have been monitored adequately.

A further refinement of the invention provides for the information for influencing the insertion of the interruption phases and information about second and/or third base stations to be transmitted by means of the same message.

This makes it possible to monitor adjacent base stations and to transmit information about the monitoring results with as little signaling complexity as possible.

Exemplary embodiments of the invention will now be described in more detail with reference to the drawings. However, the invention is not limited to these exemplary embodiments. In the individual figures of the drawing:

Figure 1 shows an outline circuit diagram of a mobile radio system;

Figure 2 shows an outline circuit diagram of a mobile station;

Figure 3 shows a schematic illustration of the insertion of interruption phases during a transmission phase;

Figure 4 shows a schematic illustration of the synchronization scheme for GSM systems;

Figure 5 shows a schematic illustration of a design variant of the synchronization scheme according to the invention.

09057653.060701
T02090 25925860

Figure 1 shows a cellular mobile radio network which, for example, comprises a combination of a GSM (Global System for Mobile Communication) system with a UMTS (Universal Mobile Telecommunication System) system, and
5 which comprises a large number of mobile switching centers MSC which are networked with one another and allow access to a landline network PSDN/ISDN. Furthermore, these mobile switching centers MSC are each connected to at least one base station controller
10 BSC, which may also be in the form of a data processing system.

Each base station controller BSC is in turn connected to at least one base station BS. Such a base station BS is a radio station which can set up a radio
15 link to other radio stations, so-called mobile stations MS, via a radio interface. Information can be transmitted within radio channels, which are within frequency bands, by means of radio signals between the mobile stations MS and the base station BS associated
20 with these mobile stations MS. The range of the radio signals from a base station essentially define a radio cell FZ.

Base stations BS and a base station controller BSC can be combined to form a base station system. The
25 base station system BSS is in this case also responsible for radio channel administration and allocation, data rate adaptation, monitoring of the radio transmission path, handover procedure and, in the case of a CDMA system, for allocation of the spread
30 code sets to be used, and transmits the signaling information required for these purposes to the mobile stations MS.

In the case of a duplex system, different frequency bands may be provided for the uplink (mobile
35 station to base station) than for the downlink (base station to mobile station) in FDD (Frequency Division Duplex) systems such as the GSM system, and different

09837653.060701
FD090" 559/5860

GR 98 P 5883
Foreign Version

- 6a -

time intervals may be provided for the uplink and
downlink

09057653-060701
FDZ090-55975860

5

10.

25

30

35

procedures, and is also responsible for changing the appliance to different operating modes.

The processing device VE may also be in the form of a digital signal processor DSP, which can
5 likewise access memory modules SPE.

The volatile or non-volatile memory modules SPE are used to store the program data required for controlling the radio station and the communication process, in particular the signaling procedures as
10 well, appliance information, information entered by the user, and information that arises during the processing of signals.

The radio-frequency section HF comprises the transmitting device SE, with a modulator and an
15 amplifier, and a receiving device EE, with a demodulator and, likewise, an amplifier.

The transmitting device SE and the receiving device EE are supplied via the synthesizer SYN with the frequency from a voltage-controlled oscillator VCO. The
20 voltage-controlled oscillator VCO also allows production of the system clock, which acts as the clock for the processor devices in the appliance.

An antenna device ANT is provided for receiving and for transmitting signals via the air interface of a
25 mobile radio system.

The radio station may also be a base station BS. In this case, the control unit is replaced by a connection to a mobile radio network, for example via a base station controller BSC and/or a switching device
30 MSC. In order to interchange data at the same time with a number of mobile stations MS, the base station BS has a corresponding large number of transmitting and receiving devices.

0985753-050701

Figure 3 shows the frame structure for a data transmission with a short delay time, in particular for voice transmission in a UMTS (Universal Mobile Telecommunications Systems) in which one super frame in each case contains twelve individual frames 1 for data transmission. In this case, the illustration shows, in particular, a transmission phase in the downlink from a first base station BS1, in particular a UMTS base station BS1, to a mobile station MS, in particular a dual-mode mobile station MS, which is designed not only to receive UMTS data but also to receive GSM data packets. The statements made in the following text are essentially limited to the downlink. However, it goes without saying that the invention can be incorporated not only in downlink transmission, but also in uplink transmission. The exemplary embodiments described in the following text for the downlink can be incorporated in an uplink transmission within the scope of a person skilled in the art.

The individual frames 1 each have a transmission length T_f of 10 ms, so that the super frame has a total transmission length T_s of 120 ms. The fifth and sixth individual frames 1 each have a common interruption phase 2, which may overlap their frame boundary 3 and has a length T_i . The length T_i is, for example, 6 ms. The subsections of the first frame 4a, which starts before the interruption phase 2, and of the second frame 4b, which ends after the interruption phase 2, have the same length, or are of the same size. In this case, during the interruption phases, at least the transmission of data to a specific mobile station which is carrying out the adjacent channel search is interrupted, while the transmission to other base stations can be continued, this being possible due to the use of a multiple access method, for example a CDMA method.

In the exemplary embodiment shown in Figure 3, voice data are being transmitted, so that a maximum

09857653.060701

GR 98 P 5883
Foreign Version

- 9a -

delay in the evaluation of the data received by the
mobile station amounting

09857653 .060701

to 10 ms, that is to say to a frame length T_f , is acceptable. The data within a frame are reorganized, jointly coded, and transmitted superimposed on one another. In the exemplary embodiment, the transmission
5 rate for the first frame 4a and for the second frame 4b are each increased in such a manner that the same amount of information to be transmitted, and which is transmitted in uncompressed frames 1 with the frame length T_f , is transmitted in a time period
10 $T_c = T_f - T_i/2$.

The following text uses Figure 4 to explain, briefly, the conventional GSM synchronization and adjacent channel search scheme. A GSM frame transmitted by the GSM base station contains eight timeslots, each
15 of which contains a data packet dp. The data packets transmitted by the GSM base stations BS2, such as the frequency correction data packet FB (characteristic data packet, FCCH data packet, Frequency Correction Burst), the synchronization data packet SB (the data
20 packet which is to be detected, SCH data packet, Synchronization Burst) and the normal data packet are all subject to the same time pattern.

A GSM super frame structure comprises 26 GSM frames 5 and lasts for 120 ms. During this GSM super
25 frame structure, an idle period is inserted into the downlink, being provided for measurements, such as the adjacent channel search.

A frequency correction data packet, followed one time frame later in each case by a synchronization
30 data packet, are transmitted by the GSM base stations four times every 10 time frames (GSM frames), and then after 11 time frames (GSM frames) (a total of 51 time frames). If interruption phases in accordance with the GSM Standard and having a period of 26 time frames (GSM
35 frames) were now to be inserted, then the fact that the period of 51 time frames and the period of 26 time frames do not have a common denominator means that the two time frame periods would be shifted cyclically so

09857653.060701

GR 98 P 5883
Foreign Version

- 10a -

that the SCH data pack sought and to be detected will
be received

09857653 060701

after a maximum of 11 times 26 time frames, that is to say after 11 monitoring frames, provided the mobile station MS is not too far away from the respective adjacent base station BS2, BS3, and excessive interference does not occur in the transmission. The FCCH is arranged in frame numbers 0, 10, 20, 30 and 40. The adjacent channel search also has the aim of detecting a synchronization data packet which is to be detected. This aim can also be achieved by receiving a characteristic frequency correction data packet since, owing to the known frame structure, the position of a synchronization data packet is known once a frequency correction data packet has been received. The mobile station thus initially searches for the FCCH data packet FB 6 until, after a successful search 7, it is switched 8 to reception of the SCH data packet in the next idle period.

For the purposes of the application, the term monitoring frame also means a time period which is the minimum required to monitor a GSM frame. The precise duration of a monitoring frame is in this case a function of the implementation; however, in order to ensure complete detection of a GSM frame and in order to take account of the time required for switching the synthesizer frequency, it is generally longer than the duration of a GSM frame, and may thus also have a duration of 9 timeslots, 10 timeslots (5.7 ms), 11 timeslots or 12 timeslots (6.9 ms).

The same scheme can also be used for the adjacent channel search or for synchronization with GSM base stations during a UMTS link, with the idle periods being replaced by interruption phases, which are inserted into the UMTS downlink data stream.

The number of interruption phases which are required in order to find a FCCH data packet depends on the repetition rate of the FCCH data packets. If the number of FCCH data packets on the GSM carrier could be doubled, then

0985753.060701

the search time would be halved. However, it is probably no longer possible to introduce such a change into the existing GSM system. However, there is no need to double the number of FCCH data packets which are transmitted by means of a GSM super frame, but it is sufficient to ensure that twice as many data packets can be used for the purpose of synchronization, irrespective of the purpose for which these data packets are actually transmitted.

Like the FCCH data packet, the SCH data packet has a pronounced training sequence which can be used for synchronization methods which use a correlation method. With conventional synchronization methods, this training sequence is used only to correlate the sequence over a narrow range, for example of 20 bits, corresponding to the time uncertainty with which FCCH data packet timing can be defined. However, this correlation can also be extended to a longer time interval, for example to the entire interval of an interruption phase. This allows the SCH data packet to carry out the function of the FCCH data packet and SCH data packet, that is to say they can be used for rough detection and for fine, bit-accurate timing detection as well as for information detection.

Switching the mobile station to exclusive reception of the SCH data packet instead of the FCCH data packet for synchronization would result in only a minor improvement since, as soon as the SCH data packet is detected all the necessary information would be available while, in contrast, after detection of an FCCH data packet, it will still be necessary to detect the corresponding SCH data packet which is transmitted 120 ms later, which means that the average detection time would be increased by this period.

35

09057653 060701

If, as explained in Figure 5, both the FCCH data packet FB and the SCH data packet SB are used 9 in parallel for synchronization, then a search speed that is twice that of the known methods can be achieved by doubling
5 the number of FCCH data packets.

Alternatively, the same search speed as that with conventional methods can be achieved despite the number or the duration of the interruption phases to be inserted being halved.

10 In general, irrespective of the duration and the number of interruption phases, the invention allows the maximum effective total duration of the interruption phases to be roughly halved.

The reasons why this newly proposed
15 synchronization scheme could not be used until now are not related to GSM synchronization during a UMTS link, since the mobile station can set its oscillator on the basis of the signals which are received by the UMTS base station and the frequency error is in consequence
20 relatively low, and because UMTS mobile stations are in any case equipped with powerful correlators for Rake processing, which are not used during the interruption phases and can thus be used for correlation of the SCH training sequence. At least in the initial
25 synchronization, a GSM station often has a considerable frequency error of several KHz. In this case, the detection process by means of correlation with a known training sequence does not work particularly well, and it is thus necessary to use different methods, which
30 are suitable only for the FC burst. Furthermore, the computation power required for correlation with the training sequence in the SC burst could not be implemented economically in a mobile station when GSM was introduced, but this is no longer a problem now due
35 to progress in processor development, and since a UMTS station requires powerful correlators in any case.

09857653.060701

For example, while the mobile station MS is in the call mode or in the user data transmission mode with a current UMTS base station BS1, the interruption phases are inserted into the downlink transmission at specific times/in specific time periods, between which there can be fixed time intervals or time intervals of different length, and, during this transmission period, the receiving device in the mobile station MS is switched to reception of data packets from respectively adjacent GSM base stations BS2, BS3.

Thus, during the interruption phase 2, the UMTS base station interrupts the transmission of data to the mobile station MS, and the mobile station MS interrupts the reception of data which are transmitted by the UMTS base station BS1. The mobile station MS uses the receiving device EE to carry out an adjacent channel search by the control device STE switching the receiving device EE to reception of adjacent GSM base stations BS2, in order to receive any synchronization data packets SB and frequency correction data packets FB which may occur and are transmitted by adjacent GSM base stations BS2, BS3.

The expression "the mobile station is switched to reception of data packets which are to be detected and to reception of characteristic data packets" also means, for the purposes of this application, that, after the normal analogue and digital filtering and, possibly, after derotation, the received data packet is compared (for example correlated) both with correlation sequence corresponding to the training sequence of a characteristic data packet and with correlation sequence corresponding to the training sequence of a data packet which is to be detected, and a simultaneous or parallel search is thus carried out for data packets which are to be detected and for characteristic data packets. Other methods may also possibly be used instead of a correlation (for example FIR, IRR or other filters).

09857653 060701

Since a large number of different versions are possible for inserting interruption phases for the purpose of adjacent channel searches, the expression "maximum effective total duration of the interruption phases" means, for the purposes of this application, the total of all the interruption phases inserted, as a maximum, for monitoring an adjacent base station. However, this does not preclude the possibility of further interruption phases being inserted when the adjacent channel search is subsequently repeated, although a new effective total duration of the interruption phases is formed in this case. The individual interruption phases may in this case each have the same duration as a monitoring frame, but may alternatively have any desired different duration. The duration of an interruption phase may also be a multiple or a fraction of the duration of a monitoring frame. It is also possible for the individual interruption phases to be of different durations.

One design version of the invention provides for an interruption phase, during which the adjacent channel search is carried out, to be inserted into the UMTS downlink transmission every 104 GSM frames or every 480 ms, rather than every 26 GSM frames (120 ms) as is normal in the GSM system, which may correspond to a different number of frames in a system other than the GSM system, in particular a CDMA system. Although only a quarter of the number of interruptions required in the prior art are required in this case, half the search speed is achieved.

Instead of having to insert an interruption phase every 104 GSM frames or every 480 ms, it has also been found in the case of complex stimulation that it is particularly advantageous to insert interruption phases every 39 GSM frames, or every 180 ms.

According to a further design version, the interruptions are repeated after 47 and 57 GSM frames, respectively, that is to say the interval between the

09857653-060701
T07090" E5975860

GR 98 P 5883
Foreign Version

- 15a -

first and second interruption (between the start of the
first and the start of the second interruption phase)
(1-2) and between the third and the fourth interruption

09857653-060701
T07090" E59Z5850

10

15

20

25

30

35

base station BS1, the UMTS base station. Then, initially, the UMTS base station does not insert any further interruption phases into the downlink data stream d.

5 Since, in the GSM system, the frequency correction data packets are transmitted by the base stations BS2, BS3 one time frame before the synchronization data packets, it is possible, after reception of a characteristic frequency correction data
10 packet FB 11, for the mobile station MS to transmit to the UMTS base station BS1 information which initially results in only one further interruption phase being inserted into the transmitted data stream, in order to receive the synchronization data packet which follows
15 the frequency correction data packet at a fixed interval. Based on the knowledge of the relative timing between the frequency correction data packet and the synchronization data packet, the timing of the interruption phases to be inserted can be matched to
20 the timing of the synchronization data packet which is to be detected.

Alternatively, in one design version, once a frequency correction data packet has been received, the interruption phases may continue to be inserted, with
25 the mobile station only switched to reception of synchronization data packets during the interruption phase, or during the time period, in which a synchronization data packet SB is transmitted.

One design version of the invention provides,
30 first of all, for switching to a monitoring of a first adjacent GSM base station BS1 and, once a successful search has been carried out or once it is known that the search has been unsuccessful, the adjacent channel search is carried for one or more further GSM base
35 stations BS3 and, after successful and/or unsuccessful completion of the adjacent channel search for a number of adjacent GSM base stations BS2, BS3, information m is transmitted to the UMTS base station BS1 for

09057653-1060701

GR 98 P 5883
Foreign Version

- 17a -

influencing and/or restricting and/or ending and/or
controlled continuation

09857653 .060701
T0/090" 559/5860

of the insertion of interruption phases. For this purpose, the initially determined results of the adjacent channel search are temporarily stored in the mobile station MS by means of memory devices SPE.

5 In one development of the invention, the results of the adjacent channel search, for example the identity of the adjacent base station and the reception quality or field strength of the signals received from the adjacent base stations, are transmitted to the UMTS
10 base station together with the information for influencing the insertion of interruption phases, as a message which, if necessary, can be split between a number of frames.

 If, in one design version of the invention, the
15 mobile station MS receives a synchronization data packet which is to be detected in one of these interruption phases, then the adjacent channel search is ended, at least with regard to this base station BS2, and the mobile station MS transmits appropriate
20 control information m to the first base station BS1, the UMTS base station. Then, initially, the UMTS base station does not insert any further interruption phases into the downlink data stream d. This allows the effective total duration of the interruption phases to
25 be reduced further.

 One development of the invention provides for elements of the digital signal processing in the mobile station to be switched off in interruption phases in which the mobile station is not switched to reception
30 of data packets on the basis that sufficient information is already available about the adjacent base stations, and thus for the power consumption of the mobile station to be reduced.

 In another design version of the invention, the
35 first base station BS1 is also a GSM base station which transmits data in accordance with a GSM Standard, or with a standard derived from it.

09057653.060701
10/09/00 15:59:58

In another design version of the invention, the first base station BS1 also is any desired base station which transmits data in accordance with a standard other than the GSM Standard, in particular in accordance with a
5 standard based on a CDMA (Code Division Multiple Access System) method.

09857653 1060701